

Package ‘timsac’

March 25, 2026

Version 1.3.8-6

Title Time Series Analysis and Control Package

Author Yoshinori Kawasaki [aut, cre],
Junji Nakano [aut],
Masami Saga [aut],
The Institute of Statistical Mathematics [cph, fnd]

Maintainer Yoshinori Kawasaki <kawasaki@ism.ac.jp>

Copyright file COPYRIGHTS

Depends R (>= 4.0.0)

Imports graphics, grDevices, stats

Description Functions for statistical analysis, prediction and control of time series based mainly on Akaike and Nakagawa (1988) <ISBN 978-90-277-2786-2>.

License GPL (>= 2)

NeedsCompilation yes

Repository CRAN

Date/Publication 2026-03-25 08:30:03 UTC

Contents

timsac-package	3
Airpollution	3
Amerikamaru	4
armafit	4
auspec	5
autcor	6
autoarmafit	7
baysea	8
bispec	10
bispecData	11
blocar	12
blomar	13
Blsallfood	14

bsubst	15
Canadianlynx	17
canarm	18
canoca	19
covgen	21
decomp	21
exsar	24
fftcor	25
fpeaut	26
fpec	27
LaborData	28
locarData	29
markov	29
mfilter	31
mlocar	32
mlomar	34
mulbar	35
mulcor	37
mulfrf	38
mulmar	39
mulnos	41
mulrsp	42
mulspe	43
nonst	45
nonstData	46
optdes	46
optsim	47
perars	49
plot.decomp	50
plot.specmx	51
Powerplant	51
prdctr	52
raspec	53
sglfre	54
simcon	55
thirmo	57
unibar	58
unimar	60
wnoise	61
xsarma	62

timsac-package

Time Series Analysis and Control Program Package

Description

R functions for statistical analysis and control of time series.

Details

This package provides functions for statistical analysis, prediction and control of time series. The original TIMSAC (TIME Series Analysis and Control) or TIMSAC-72 was published in Akaike and Nakagawa (1972). After that, TIMSAC-74, TIMSAC-78 and TIMSAC-84 were published as the TIMSAC series in Computer Science Monograph.

For overview of models and information criteria for model selection, see [../doc/timsac-guide_e.pdf](#) or [../doc/timsac-guide_j.pdf](#) (in Japanese).

References

H.Akaike, E.Arahata and T.Ozaki (1975) *Computer Science Monograph, No.5, Timsac74, A Time Series Analysis and Control Program Package (1)*. The Institute of Statistical Mathematics.

H.Akaike, E.Arahata and T.Ozaki (1975) *Computer Science Monograph, No.6, Timsac74, A Time Series Analysis and Control Program Package (2)*. The Institute of Statistical Mathematics.

H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Timsac78*. The Institute of Statistical Mathematics.

H.Akaike, T.Ozaki, M.Ishiguro, Y.Ogata, G.Kitagawa, Y-H.Tamura, E.Arahata, K.Katsura and Y.Tamura (1985) *Computer Science Monograph, No.22, Timsac84 Part 1*. The Institute of Statistical Mathematics.

H.Akaike and T.Nakagawa (1988) *Statistical Analysis and Control of Dynamic Systems*. Kluwer Academic publishers.

Airpollution

Airpollution Data

Description

An airpollution data for testing [perars](#).

Usage

```
data(Airpollution)
```

Format

A time series of 372 observations.

Source

H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Tim-sac78*. The Institute of Statistical Mathematics.

Amerikamaru

Amerikamaru Data

Description

A multivariate non-stationary data for testing [blomar](#).

Usage

```
data(Amerikamaru)
```

Format

A 2-dimensional array with 896 observations on 2 variables.

```
[, 1]  rudder  
[, 2]  yawing
```

Source

H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Tim-sac78*. The Institute of Statistical Mathematics.

armafit

ARMA Model Fitting

Description

Fit an ARMA model with specified order by using DAVIDON's algorithm.

Usage

```
armafit(y, model.order)
```

Arguments

y	a univariate time series.
model.order	a numerical vector of the form c(ar, ma) which gives the order to be fitted successively.

Details

The maximum likelihood estimates of the coefficients of a scalar ARMA model

$$y(t) - a(1)y(t-1) - \dots - a(p)y(t-p) = u(t) - b(1)u(t-1) - \dots - b(q)u(t-q)$$

of a time series $y(t)$ are obtained by using DAVIDON's algorithm. Pure autoregression is not allowed.

Value

arcoef	maximum likelihood estimates of AR coefficients.
macoef	maximum likelihood estimates of MA coefficients.
arstd	standard deviation (AR).
mastd	standard deviation (MA).
v	innovation variance.
aic	AIC.
grad	final gradient.

References

H.Akaike, E.Arahata and T.Ozaki (1975) *Computer Science Monograph, No.5, Timsac74, A Time Series Analysis and Control Program Package (1)*. The Institute of Statistical Mathematics.

Examples

```
# "arma.sim" is a function in "stats".
# Note that the sign of MA coefficient is opposite from that in "timsac".
y <- arima.sim(list(order=c(2,0,1), ar=c(0.64,-0.8), ma=-0.5), n = 1000)
z <- armafit(y, model.order = c(2,1))
z$arcoef
z$macoef
```

auspec

Power Spectrum

Description

Compute power spectrum estimates for two trigonometric windows of Blackman-Tukey type by Goertzel method.

Usage

```
auspec(y, lag = NULL, window = "Akaike", log = FALSE, plot = TRUE)
```

Arguments

<code>y</code>	a univariate time series.
<code>lag</code>	maximum lag. Default is $2\sqrt{n}$, where n is the length of time series y .
<code>window</code>	character string giving the definition of smoothing window. Allowed strings are "Akaike" (default) or "Hanning".
<code>log</code>	logical. If TRUE, the spectrum <code>spec</code> is plotted as $\log(\text{spec})$.
<code>plot</code>	logical. If TRUE (default), the spectrum <code>spec</code> is plotted.

Details

Hanning Window : $a_1(0)=0.5, \quad a_1(1)=a_1(-1)=0.25, \quad a_1(2)=a_1(-2)=0$
 Akaike Window : $a_2(0)=0.625, \quad a_2(1)=a_2(-1)=0.25, \quad a_2(2)=a_2(-2)=-0.0625$

Value

<code>spec</code>	spectrum smoothing by 'window'
<code>stat</code>	test statistics.

References

H.Akaike and T.Nakagawa (1988) *Statistical Analysis and Control of Dynamic Systems*. Kluwer Academic publishers.

Examples

```
y <- arima.sim(list(order=c(2,0,0), ar=c(0.64,-0.8)), n = 200)
auspec(y, log = TRUE)
```

autcor *Autocorrelation*

Description

Estimate autocovariances and autocorrelations.

Usage

```
autcor(y, lag = NULL, plot = TRUE, lag_axis = TRUE)
```

Arguments

<code>y</code>	a univariate time series.
<code>lag</code>	maximum lag. Default is $2\sqrt{n}$, where n is the length of the time series y .
<code>plot</code>	logical. If TRUE (default), autocorrelations are plotted.
<code>lag_axis</code>	logical. If TRUE (default) with <code>plot = TRUE</code> , x -axis is drawn.

Value

acov	autocovariances.
acor	autocorrelations (normalized covariances).
mean	mean of y .

References

H.Akaike and T.Nakagawa (1988) *Statistical Analysis and Control of Dynamic Systems*. Kluwer Academic publishers.

Examples

```
# Example 1 for the normal distribution
y <- rnorm(200)
autcor(y, lag_axis = FALSE)

# Example 2 for the ARIMA model
y <- arima.sim(list(order=c(2,0,0), ar=c(0.64,-0.8)), n = 200)
autcor(y, lag = 20)
```

autoarmafit

Automatic ARMA Model Fitting

Description

Provide an automatic ARMA model fitting procedure. Models with various orders are fitted and the best choice is determined with the aid of the statistics AIC.

Usage

```
autoarmafit(y, max.order = NULL)
```

Arguments

y	a univariate time series.
max.order	upper limit of AR order and MA order. Default is $2\sqrt{n}$, where n is the length of the time series y .

Details

The maximum likelihood estimates of the coefficients of a scalar ARMA model

$$y(t) - a(1)y(t-1) - \dots - a(p)y(t-p) = u(t) - b(1)u(t-1) - \dots - b(q)u(t-q)$$

of a time series $y(t)$ are obtained by using DAVIDON's variance algorithm. Where p is AR order, q is MA order and $u(t)$ is a zero mean white noise. Pure autoregression is not allowed.

Value

best.model the best choice of ARMA coefficients.

model a list with components arcoef (Maximum likelihood estimates of AR coefficients), macoef (Maximum likelihood estimates of MA coefficients), arstd (AR standard deviation), mastd (MA standard deviation), v (Innovation variance), aic ($AIC = n \log(\det(v)) + 2(p + q)$) and grad (Final gradient) in AIC increasing order.

References

H.Akaike, E.Arahata and T.Ozaki (1975) *Computer Science Monograph, No.5, Timsac74, A Time Series Analysis and Control Program Package (I)*. The Institute of Statistical Mathematics.

Examples

```
# "arima.sim" is a function in "stats".
# Note that the sign of MA coefficient is opposite from that in "timsac".
y <- arima.sim(list(order=c(2,0,1),ar=c(0.64,-0.8),ma=-0.5), n = 1000)
autoarmafit(y)
```

 baysea

Bayesian Seasonal Adjustment Procedure

Description

Decompose a nonstationary time series into several possible components.

Usage

```
baysea(y, period = 12, span = 4, shift = 1, forecast = 0, trend.order = 2,
       seasonal.order = 1, year = 0, month = 1, out = 0, rigid = 1,
       zersum = 1, delta = 7, alpha = 0.01, beta = 0.01, gamma = 0.1,
       spec = TRUE, plot = TRUE, separate.graphics = FALSE)
```

Arguments

y a univariate time series.

period number of seasonals within a period.

span number of periods to be processed at one time.

shift number of periods to be shifted to define the new span of data.

forecast length of forecast at the end of data.

trend.order order of differencing of trend.

seasonal.order order of differencing of seasonal. seasonal.order is smaller than or equal to span.

year	trading-day adjustment option. = 0 : without trading day adjustment > 0 : with trading day adjustment (the series is supposed to start at this year)
month	number of the month in which the series starts. If year=0 this parameter is ignored.
out	outlier correction option. 0 : without outlier detection 1 : with outlier detection by marginal probability 2 : with outlier detection by model selection
rigid	controls the rigidity of the seasonal component. more rigid seasonal with larger than rigid.
zerset	controls the sum of the seasonals within a period.
delta	controls the leap year effect.
alpha	controls prior variance of initial trend.
beta	controls prior variance of initial seasonal.
gamma	controls prior variance of initial sum of seasonal.
spec	logical. If TRUE (default), estimate spectra of irregular and differenced adjusted.
plot	logical. If TRUE (default), plot trend, adjust, smoothed, season and irregular.
separate.graphics	logical. If TRUE, a graphic device is opened for each graphics display.

Details

This function realized a decomposition of time series y into the form

$$y(t) = T(t) + S(t) + I(t) + TDC(t) + OCF(t)$$

where $T(t)$ is trend component, $S(t)$ is seasonal component, $I(t)$ is irregular, $TDC(t)$ is trading day factor and $OCF(t)$ is outlier correction factor. For the purpose of comparison of models the criterion ABIC is defined

$$ABIC = -2 \log(\text{maximum likelihood of the model}).$$

Smaller value of ABIC represents better fit.

Value

outlier	outlier correction factor.
trend	trend.
season	seasonal.
tday	trading day component if year > 0.

irregular = y - trend - season - tday - outlier.
 adjust = trend - irregular.
 smoothed = trend + season + tday.
 aveABIC averaged ABIC.
 irregular.spec a list with components acov (autocovariances), acor (normalized covariances), mean, v (innovation variance), aic (AIC), parcor (partial autocorrelation) and rspec (rational spectrum) of irregular if spec = TRUE.
 adjusted.spec a list with components acov, acor, mean, v, aic, parcor and rspec of differenced adjusted series if spec = TRUE.
 differenced.trend a list with components acov, acor, mean, v, aic and parcor of differenced trend series if spec = TRUE.
 differenced.season a list with components acov, acor, mean, v, aic and parcor of differenced seasonal series if spec = TRUE.

References

H.Akaike, T.Ozaki, M.Ishiguro, Y.Ogata, G.Kitagawa, Y-H.Tamura, E.Arahata, K.Katsura and Y.Tamura (1985) *Computer Science Monograph, No.22, Timsac84 Part 1*. The Institute of Statistical Mathematics.

Examples

```
data(LaborData)
baysea(LaborData, forecast = 12)
```

bispec	<i>Bispectrum</i>
--------	-------------------

Description

Compute bi-spectrum using the direct Fourier transform of sample third order moments.

Usage

```
bispec(y, lag = NULL, window = "Akaike", log = FALSE, plot = TRUE)
```

Arguments

y a univariate time series.
 lag maximum lag. Default is $2\sqrt{n}$, where n is the length of the time series y .
 window character string giving the definition of smoothing window. Allowed strings are "Akaike" (default) or "Hanning".
 log logical. If TRUE, the spectrum pspec is plotted as $\log(\text{pspec})$.
 plot logical. If TRUE (default), the spectrum pspec is plotted.

Details

Hanning Window : $a_1(0)=0.5$, $a_1(1)=a_1(-1)=0.25$, $a_1(2)=a_1(-2)=0$
 Akaike Window : $a_2(0)=0.625$, $a_2(1)=a_2(-1)=0.25$, $a_2(2)=a_2(-2)=-0.0625$

Value

pspec power spectrum smoothed by 'window'.
 sig significance.
 cohe coherence.
 breal real part of bispectrum.
 bimag imaginary part of bispectrum.
 exval approximate expected value of coherence under Gaussian assumption.

References

H.Akaike, E.Arahata and T.Ozaki (1975) *Computer Science Monograph, No.6, Timsac74, A Time Series Analysis and Control Program Package (2)*. The Institute of Statistical Mathematics.

Examples

```
data(bispecData)
bispec(bispecData, lag = 30)
```

bispecData	<i>Univariate Test Data</i>
------------	-----------------------------

Description

A univariate data for testing [bispec](#) and [thirmo](#).

Usage

```
data(bispecData)
```

Format

A time series of 1500 observations.

Source

H.Akaike, E.Arahata and T.Ozaki (1976) *Computer Science Monograph, No.6, Timsac74 A Time Series Analysis and Control Program Package (2)*. The Institute of Statistical Mathematics.

 blocar

Bayesian Method of Locally Stationary AR Model Fitting; Scalar Case

Description

Locally fit autoregressive models to non-stationary time series by a Bayesian procedure.

Usage

```
blocar(y, max.order = NULL, span, plot = TRUE)
```

Arguments

<code>y</code>	a univariate time series.
<code>max.order</code>	upper limit of the order of AR model. Default is $2\sqrt{n}$, where n is the length of the time series y .
<code>span</code>	length of basic local span.
<code>plot</code>	logical. If TRUE (default), spectrums <code>pspec</code> are plotted.

Details

The basic AR model of scalar time series $y(t) (t = 1, \dots, n)$ is given by

$$y(t) = a(1)y(t-1) + a(2)y(t-2) + \dots + a(p)y(t-p) + u(t),$$

where p is order of the model and $u(t)$ is Gaussian white noise with mean 0 and variance v . At each stage of modeling of locally AR model, a two-step Bayesian procedure is applied

1. Averaging of the models with different orders fitted to the newly obtained data.
2. Averaging of the models fitted to the present and preceding spans.

AIC of the model fitted to the new span is defined by

$$AIC = ns \log(sd) + 2k,$$

where ns is the length of new data, sd is innovation variance and k is the equivalent number of parameters, defined as the sum of squares of the Bayesian weights. AIC of the model fitted to the preceding spans are defined by

$$AIC(j+1) = ns \log(sd(j)) + 2,$$

where $sd(j)$ is the prediction error variance by the model fitted to j periods former span.

Value

var	variance.
aic	AIC.
bweight	Bayesian weight.
pacoef	partial autocorrelation.
arcoef	coefficients (average by the Bayesian weights).
v	innovation variance.
init	initial point of the data fitted to the current model.
end	end point of the data fitted to the current model.
pspec	power spectrum.

References

G.Kitagawa and H.Akaike (1978) A Procedure for The Modeling of Non-Stationary Time Series. Ann. Inst. Statist. Math., 30, B, 351–363.

H.Akaike (1978) A Bayesian Extension of the Minimum AIC Procedure of Autoregressive Model Fitting. Research Memo. NO.126. The Institute of The Statistical Mathematics.

H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Tim-sac78*. The Institute of Statistical Mathematics.

Examples

```
data(locarData)
z <- blocar(locarData, max.order = 10, span = 300)
z$arcoef
```

blomar *Bayesian Method of Locally Stationary Multivariate AR Model Fitting*

Description

Locally fit multivariate autoregressive models to non-stationary time series by a Bayesian procedure.

Usage

```
blomar(y, max.order = NULL, span)
```

Arguments

y	A multivariate time series.
max.order	upper limit of the order of AR model, less than or equal to $n/2d$ where n is the length and d is the dimension of the time series y . Default is $\min(2\sqrt{n}, n/2d)$.
span	length of basic local span. Let m denote max.order, if $n - m - 1$ is less than or equal to span or $n - m - 1 - \text{span}$ is less than $2md$, span is $n - m$.

Details

The basic AR model is given by

$$y(t) = A(1)y(t-1) + A(2)y(t-2) + \dots + A(p)y(t-p) + u(t),$$

where p is order of the AR model and $u(t)$ is innovation variance v .

Value

mean	mean.
var	variance.
bweight	Bayesian weight.
aic	AIC with respect to the present data.
arcoef	AR coefficients. <code>arcoef[[m]][i,j,k]</code> shows the value of i -th row, j -th column, k -th order of m -th model.
v	innovation variance.
eaic	equivalent AIC of Bayesian model.
init	start point of the data fitted to the current model.
end	end point of the data fitted to the current model.

References

- G.Kitagawa and H.Akaike (1978) A Procedure for the Modeling of Non-stationary Time Series. *Ann. Inst. Statist. Math.*, 30, B, 351–363.
- H.Akaike (1978) A Bayesian Extension of The Minimum AIC Procedure of Autoregressive Model Fitting. Research Memo. NO.126. The institute of Statistical Mathematics.
- H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Tim-sac78*. The Institute of Statistical Mathematics.

Examples

```
data(Amerikamaru)
blomar(Amerikamaru, max.order = 10, span = 300)
```

Blsallfood

Blsallfood Data

Description

The BLSALLFOOD data. (the Bureau of Labor Statistics, all employees in food industries, January 1967 - December 1979)

Usage

```
data(Blsallfood)
```

Format

A time series of 156 observations.

Source

H.Akaike, T.Ozaki, M.Ishiguro, Y.Ogata, G.Kitagawa, Y-H.Tamura, E.Arahata, K.Katsura and Y.Tamura (1984) *Computer Science Monographs, Timsac-84 Part 1*. The Institute of Statistical Mathematics.

bsubst

Bayesian Type All Subset Analysis

Description

Produce Bayesian estimates of time series models such as pure AR models, AR models with non-linear terms, AR models with polynomial type mean value functions, etc. The goodness of fit of a model is checked by the analysis of several steps ahead prediction errors.

Usage

```
bsubst(y, mtype, lag = NULL, nreg, reg = NULL, term.lag = NULL, cstep = 5,
      plot = TRUE)
```

Arguments

y	a univariate time series.
mtype	model type. Allowed values are <ul style="list-style-type: none"> 1 : autoregressive model, 2 : polynomial type non-linear model (lag's read in), 3 : polynomial type non-linear model (lag's automatically set), 4 : AR-model with polynomial mean value function, 5,6,7 : originally defined but omitted here.
lag	maximum time lag. Default is $2\sqrt{n}$, where n is the length of the time series y .
nreg	number of regressors.
reg	specification of regressor ($mtype = 2$). i -th regressor is defined by $z(n - L1(i)) \times z(n - L2(i)) \times z(n - L3(i))$, where $L1(i)$ is $reg(1, i)$, $L2(i)$ is $reg(2, i)$ and $L3(i)$ is $reg(3, i)$. 0-lag term $z(n - 0)$ is replaced by the constant 1.
term.lag	maximum time lag specify the regressors ($L1(i), L2(i), L3(i)$) ($i=1, \dots, nreg$) ($mtype = 3$). <ul style="list-style-type: none"> term.lag[1] : maximum time lag of linear term term.lag[2] : maximum time lag of squared term

	term.lag[3] :	maximum time lag of quadratic crosses term
	term.lag[4] :	maximum time lag of cubic term
	term.lag[5] :	maximum time lag of cubic cross term.
cstep		prediction errors checking (up to cstep-steps ahead) is requested. (mtype = 1, 2, 3).
plot		logical. If TRUE (default), daic, perr and peautcor are plotted.

Details

The AR model is given by (mtype = 2)

$$y(t) = a(1)y(t-1) + \dots + a(p)y(t-p) + u(t).$$

The non-linear model is given by (mtype = 2, 3)

$$y(t) = a(1)z(t,1) + a(2)z(t,2) + \dots + a(p)z(t,p) + u(t).$$

Where p is AR order and $u(t)$ is Gaussian white noise with mean 0 and variance $v(p)$.

Value

ymean	mean of y.
yvar	variance of y.
v	innovation variance.
aic	AIC(m), (m=0, ... nreg).
aicmin	minimum AIC.
daic	AIC(m)-aicmin (m=0, ... nreg).
order.maice	order of minimum AIC.
v.maice	innovation variance attained at order.maice.
arcoef.maice	AR coefficients attained at order.maice.
v.bay	residual variance of Bayesian model.
aic.bay	AIC of Bayesian model.
np.bay	equivalent number of parameters.
arcoef.bay	AR coefficients of Bayesian model.
ind.c	index of parcor2 in order of increasing magnitude.
parcor2	square of partial correlations (normalized by multiplying N).
damp	binomial type damper.
bweight	final Bayesian weights of partial correlations.
parcor.bay	partial correlations of the Bayesian model.
eicmin	minimum EIC.
esum	whole subset regression models.
npmean	mean of number of parameter.

npmean.nreg = npmean / nreg.
 perr prediction error.
 mean mean.
 var variance.
 skew skewness.
 peak peakedness.
 peautcor autocorrelation function of 1-step ahead prediction error.
 pspec power spectrum (mtype = 1).

References

H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Tim-sac78*. The Institute of Statistical Mathematics.

Examples

```

data(Canadianlynx)
Regressor <- matrix(
  c( 1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 11, 12, 1, 2, 1, 3, 1, 2, 3,
    0, 0, 0, 0, 0, 0, 0, 0, 0, 0, 0, 0, 1, 2, 2, 3, 1, 2, 3,
    0, 0, 0, 0, 0, 0, 0, 0, 0, 0, 0, 0, 0, 0, 0, 0, 1, 2, 3 ),
  nrow = 3, ncol = 19, byrow = TRUE)
z <- bsubst(Canadianlynx, mtype = 2, lag = 12, nreg = 19, Regressor)
z$arcoef.bay

```

Canadianlynx

Time series of Canadian lynx data

Description

A time series of Canadian lynx data for testing [unimar](#), [unibar](#), [bsubst](#) and [exsar](#).

Usage

```
data(Canadianlynx)
```

Format

A time series of 114 observations.

Source

H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Tim-sac78*. The Institute of Statistical Mathematics.

 canarm

Canonical Correlation Analysis of Scalar Time Series

Description

Fit an ARMA model to stationary scalar time series through the analysis of canonical correlations between the future and past sets of observations.

Usage

```
canarm(y, lag = NULL, max.order = NULL, plot = TRUE)
```

Arguments

y	a univariate time series.
lag	maximum lag. Default is $2\sqrt{n}$, where n is the length of the time series y .
max.order	upper limit of AR order and MA order, must be less than or equal to lag. Default is lag.
plot	logical. If TRUE (default), parcor is plotted.

Details

The ARMA model of stationary scalar time series $y(t)(t = 1, \dots, n)$ is given by

$$y(t) - a(1)y(t-1) - \dots - a(p)y(t-p) = u(t) - b(1)u(t-1) - \dots - b(q)u(t-q),$$

where p is AR order and q is MA order.

Value

arinit	AR coefficients of initial AR model fitting by the minimum AIC procedure.
v	innovation vector.
aic	AIC.
aicmin	minimum AIC.
order.maice	order of minimum AIC.
parcor	partial autocorrelation.
nc	total number of case.
future	number of present and future variables.
past	number of present and past variables.
cweight	future set canonical weight.
canocoeff	canonical R.
canocoeff2	R-squared.
chisquar	chi-square.

ndf	N.D.F.
dic	DIC.
dicmin	minimum DIC.
order.dicmin	order of minimum DIC.
arcoef	AR coefficients $a(i)(i = 1, \dots, p)$.
macoef	MA coefficients $b(i)(i = 1, \dots, q)$.

References

H.Akaike, E.Arahata and T.Ozaki (1975) *Computer Science Monograph, No.5, Timsac74, A Time Series Analysis and Control Program Package (1)*. The Institute of Statistical Mathematics.

Examples

```
# "arima.sim" is a function in "stats".
# Note that the sign of MA coefficient is opposite from that in "timsac".
y <- arima.sim(list(order=c(2,0,1), ar=c(0.64,-0.8), ma=c(-0.5)), n = 1000)
z <- canarm(y, max.order = 30)
z$arcoef
z$macoef
```

canoca

Canonical Correlation Analysis of Vector Time Series

Description

Analyze canonical correlation of a d-dimensional multivariate time series.

Usage

```
canoca(y)
```

Arguments

y a multivariate time series.

Details

First AR model is fitted by the minimum AIC procedure. The results are used to ortho-normalize the present and past variables. The present and future variables are tested successively to decide on the dependence of their predictors. When the last DIC (=chi-square - 2.0*N.D.F.) is negative the predictor of the variable is decided to be linearly dependent on the antecedents.

Value

aic	AIC.
aicmin	minimum AIC.
order.maice	MAICE AR model order.
v	innovation variance.
arcoef	autoregressive coefficients. arcoef[i,j,k] shows the value of i -th row, j -th column, k -th order.
nc	number of cases.
future	number of variable in the future set.
past	number of variables in the past set.
cweight	future set canonical weight.
canocoef	canonical R.
canocoef2	R-squared.
chisquar	chi-square.
ndf	N.D.F.
dic	DIC.
dicmin	minimum DIC.
order.dicmin	order of minimum DIC.
matF	the transition matrix F .
vectH	structural characteristic vector H of the canonical Markovian representation.
matG	the estimate of the input matrix G .
vectF	matrix F in vector form.

References

H.Akaike, E.Arahata and T.Ozaki (1975) *Computer Science Monograph, No.5, Timsac74, A Time Series Analysis and Control Program Package (1)*. The Institute of Statistical Mathematics.

Examples

```
ar <- array(0, dim = c(3,3,2))
ar[, , 1] <- matrix(c(0.4, 0, 0.3,
                    0.2, -0.1, -0.5,
                    0.3, 0.1, 0), nrow = 3, ncol = 3, byrow = TRUE)
ar[, , 2] <- matrix(c(0, -0.3, 0.5,
                    0.7, -0.4, 1,
                    0, -0.5, 0.3), nrow = 3, ncol = 3, byrow = TRUE)
x <- matrix(rnorm(1000*3), nrow = 1000, ncol = 3)
y <- mfilter(x, ar, "recursive")
z <- canoca(y)
z$arcoef
```

covgen	<i>Covariance Generation</i>
--------	------------------------------

Description

Produce the Fourier transform of a power gain function in the form of an autocovariance sequence.

Usage

```
covgen(lag, f, gain, plot = TRUE)
```

Arguments

lag	desired maximum lag of covariance.
f	frequency $f[i]$ ($i = 1, \dots, k$), where k is the number of data points. By definition $f[1] = 0.0$ and $f[k] = 0.5$, $f[i]$'s are arranged in increasing order.
gain	power gain of the filter at the frequency $f[i]$.
plot	logical. If TRUE (default), autocorrelations are plotted.

Value

acov	autocovariance.
acor	autocovariance normalized.

References

H.Akaike, E.Arahata and T.Ozaki (1975) *Computer Science Monograph, No.5, Timsac74, A Time Series Analysis and Control Program Package (1)*. The Institute of Statistical Mathematics.

Examples

```
spec <- raspec(h = 100, var = 1, arcoef = c(0.64,-0.8), plot = FALSE)
covgen(lag = 100, f = 0:100/200, gain = spec)
```

decomp	<i>Time Series Decomposition (Seasonal Adjustment) by Square-Root Filter</i>
--------	--

Description

Decompose a nonstationary time series into several possible components by square-root filter.

Usage

```
decomp(y, trend.order = 2, ar.order = 2, seasonal.order = 1,
       period = 1, log = FALSE, trade = FALSE, diff = 1,
       miss = 0, omax = 99999.9, plot = TRUE, ...)
```

Arguments

<code>y</code>	a univariate time series with or without the <code>tsp</code> attribute.
<code>trend.order</code>	trend order (1, 2 or 3).
<code>ar.order</code>	AR order (less than 11, try 2 first).
<code>seasonal.order</code>	seasonal order (0, 1 or 2).
<code>period</code>	number of seasons in one period. If the <code>tsp</code> attribute of <code>y</code> is not NULL, <code>frequency(y)</code> .
<code>log</code>	logical; if TRUE, a log scale is in use.
<code>trade</code>	logical; if TRUE, the model including trading day effect component is considered, where <code>tsp(y)</code> is not null and <code>frequency(y)</code> is 4 or 12.
<code>diff</code>	numerical differencing (1 sided or 2 sided).
<code>miss</code>	missing value flag. = 0 : no consideration > 0 : values which are greater than <code>omax</code> are treated as missing data < 0 : values which are less than <code>omax</code> are treated as missing data
<code>omax</code>	maximum or minimum data value (if <code>miss > 0</code> or <code>miss < 0</code>).
<code>plot</code>	logical. If TRUE (default), <code>trend</code> , <code>seasonal</code> , <code>ar</code> and <code>trad</code> are plotted.
<code>...</code>	graphical arguments passed to <code>plot.decomp</code> .

Details

The Basic Model

$$y(t) = T(t) + AR(t) + S(t) + TD(t) + W(t)$$

where $T(t)$ is trend component, $AR(t)$ is AR process, $S(t)$ is seasonal component, $TD(t)$ is trading day factor and $W(t)$ is observational noise.

Component Models

- Trend component (trend.order `m1`)
 - $m1 = 1 : T(t) = T(t - 1) + v1(t)$
 - $m1 = 2 : T(t) = 2T(t - 1) - T(t - 2) + v1(t)$
 - $m1 = 3 : T(t) = 3T(t - 1) - 3T(t - 2) + T(t - 2) + v1(t)$
- AR component (ar.order `m2`)
 - $AR(t) = a(1)AR(t - 1) + \dots + a(m2)AR(t - m2) + v2(t)$

- Seasonal component (seasonal.order k, frequency f)

$$k = 1 : S(t) = -S(t-1) - \dots - S(t-f+1) + v3(t)$$

$$k = 2 : S(t) = -2S(t-1) - \dots - f S(t-f+1) - \dots - S(t-2f+2) + v3(t)$$
- Trading day effect

$$TD(t) = b(1)TRADE(t,1) + \dots + b(7)TRADE(t,7)$$
 where $TRADE(t,i)$ is the number of i -th days of the week in t -th data and $b(1) + \dots + b(7) = 0$.

Value

An object of class "decomp", which is a list with the following components:

trend	trend component.
seasonal	seasonal component.
ar	AR process.
trad	trading day factor.
noise	observational noise.
aic	AIC.
lkhd	likelihood.
sigma2	sigma ² .
tau1	system noise variances $v1$.
tau2	system noise variances $v2$ or $v3$.
tau3	system noise variances $v3$.
arcoef	vector of AR coefficients.
tdf	trading day factor. tdf(i) (i=1,7) are from Sunday to Saturday sequentially.
conv.y	Missing values are replaced by NA after the specified logarithmic transformation..

References

- G.Kitagawa (1981) *A Nonstationary Time Series Model and Its Fitting by a Recursive Filter* Journal of Time Series Analysis, Vol.2, 103-116.
- W.Gersch and G.Kitagawa (1983) *The prediction of time series with Trends and Seasonalities* Journal of Business and Economic Statistics, Vol.1, 253-264.
- G.Kitagawa (1984) *A smoothness priors-state space modeling of Time Series with Trend and Seasonality* Journal of American Statistical Association, VOL.79, NO.386, 378-389.

Examples

```
data(Blsallfood)
y <- ts(Blsallfood, start=c(1967,1), frequency=12)
z <- decomp(y, trade = TRUE)
z$aic
```

z\$lkhd
 z\$sigma2
 z\$tau1
 z\$tau2
 z\$tau3

 exsar

Exact Maximum Likelihood Method of Scalar AR Model Fitting

Description

Produce exact maximum likelihood estimates of the parameters of a scalar AR model.

Usage

```
exsar(y, max.order = NULL, plot = FALSE)
```

Arguments

y	a univariate time series.
max.order	upper limit of AR order. Default is $2\sqrt{n}$, where n is the length of the time series y .
plot	logical. If TRUE, daic is plotted.

Details

The AR model is given by

$$y(t) = a(1)y(t-1) + \dots + a(p)y(t-p) + u(t)$$

where p is AR order and $u(t)$ is a zero mean white noise.

Value

mean	mean.
var	variance.
v	innovation variance.
aic	AIC.
aicmin	minimum AIC.
daic	AIC-aicmin.
order.maice	order of minimum AIC.
v.maice	MAICE innovation variance.
arcoef.maice	MAICE AR coefficients.
v.mle	maximum likelihood estimates of innovation variance.
arcoef.mle	maximum likelihood estimates of AR coefficients.

References

H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Tim-sac78*. The Institute of Statistical Mathematics.

Examples

```
data(Canadianlynx)
z <- exsar(Canadianlynx, max.order = 14)
z$arcoef.maice
z$arcoef.mle
```

fftcor

Auto And/Or Cross Correlations via FFT

Description

Compute auto and/or cross covariances and correlations via FFT.

Usage

```
fftcor(y, lag = NULL, isw = 4, plot = TRUE, lag_axis = TRUE)
```

Arguments

y	data of channel X and Y (data of channel Y is given for $isw = 2$ or 4 only).
lag	maximum lag. Default is $2\sqrt{n}$, where n is the length of the time series y .
isw	numerical flag giving the type of computation.
	1 : auto-correlation of X (one-channel)
	2 : auto-correlations of X and Y (two-channel)
	4 : auto- and cross- correlations of X and Y (two-channel)
plot	logical. If TRUE (default), cross-correlations are plotted.
lag_axis	logical. If TRUE (default) with $plot=TRUE$, x -axis is drawn.

Value

acov	auto-covariance.
ccov12	cross-covariance.
ccov21	cross-covariance.
acor	auto-correlation.
ccor12	cross-correlation.
ccor21	cross-correlation.
mean	mean.

References

H.Akaike and T.Nakagawa (1988) *Statistical Analysis and Control of Dynamic Systems*. Kluwer Academic publishers.

Examples

```
# Example 1
x <- rnorm(200)
y <- rnorm(200)
xy <- array(c(x,y), dim = c(200,2))
fftcor(xy, lag_axis = FALSE)

# Example 2
xorg <- rnorm(1003)
x <- matrix(0, nrow = 1000, ncol = 2)
x[, 1] <- xorg[1:1000]
x[, 2] <- xorg[4:1003] + 0.5*rnorm(1000)
fftcor(x, lag = 20)
```

fpeaut

FPE Auto

Description

Perform FPE(Final Prediction Error) computation for one-dimensional AR model.

Usage

```
fpeaut(y, max.order = NULL)
```

Arguments

y	a univariate time series.
max.order	upper limit of model order. Default is $2\sqrt{n}$, where n is the length of the time series y .

Details

The AR model is given by

$$y(t) = a(1)y(t-1) + \dots + a(p)y(t-p) + u(t)$$

where p is AR order and $u(t)$ is a zero mean white noise.

Value

ordermin	order of minimum FPE.
best.ar	AR coefficients with minimum FPE.
sigma2m	= sigma2(ordermin).
fpemin	minimum FPE.
rfpemin	minimum RFPE.
ofpe	OFPE.
arcoef	AR coefficients.
sigma2	σ^2 .
fpe	FPE (Final Prediction Error).
rfpe	RFPE.
parcor	partial correlation.
chi2	chi-squared.

References

H.Akaike and T.Nakagawa (1988) *Statistical Analysis and Control of Dynamic Systems*. Kluwer Academic publishers.

Examples

```
y <- arima.sim(list(order=c(2,0,0), ar=c(0.64,-0.8)), n = 200)
fpeaut(y, max.order = 20)
```

fpec *AR model Fitting for Control*

Description

Perform AR model fitting for control.

Usage

```
fpec(y, max.order = NULL, control = NULL, manip = NULL)
```

Arguments

y	a multivariate time series.
max.order	upper limit of model order. Default is $2\sqrt{n}$, where n is the length of time series y .
control	controlled variables. Default is $c(1 : d)$, where d is the dimension of the time series y .
manip	manipulated variables. Default number of manipulated variable is 0.

Value

cov	covariance matrix rearrangement.
fpec	FPEC (AR model fitting for control).
rfpec	RFPEC.
aic	AIC.
ordermin	order of minimum FPEC.
fpecmin	minimum FPEC.
rfpecmin	minimum RFPEC.
aicmin	minimum AIC.
perr	prediction error covariance matrix.
arcoef	a set of coefficient matrices. arcoef[i, j, k] shows the value of <i>i</i> -th row, <i>j</i> -th column, <i>k</i> -th order.

References

H.Akaike and T.Nakagawa (1988) *Statistical Analysis and Control of Dynamic Systems*. Kluwer Academic publishers.

Examples

```
ar <- array(0, dim = c(3,3,2))
ar[, , 1] <- matrix(c(0.4, 0, 0.3,
                    0.2, -0.1, -0.5,
                    0.3, 0.1, 0), nrow = 3, ncol = 3, byrow = TRUE)
ar[, , 2] <- matrix(c(0, -0.3, 0.5,
                    0.7, -0.4, 1,
                    0, -0.5, 0.3), nrow = 3, ncol = 3, byrow = TRUE)
x <- matrix(rnorm(200*3), nrow = 200, ncol = 3)
y <- mfilter(x, ar, "recursive")
fpec(y, max.order = 10)
```

LaborData

Labor force Data

Description

Labor force U.S. unemployed 16 years or over (1972-1978) data.

Usage

```
data(LaborData)
```

Format

A time series of 72 observations.

Source

H.Akaike, T.Ozaki, M.Ishiguro, Y.Ogata, G.Kitagawa, Y-H.Tamura, E.Arahata, K.Katsura and Y.Tamura (1985) *Computer Science Monograph, No.22, Timsac84 Part 1*. The Institute of Statistical Mathematics.

locarData	<i>Non-stationary Test Data</i>
-----------	---------------------------------

Description

A non-stationary data for testing [mlocar](#) and [blocar](#).

Usage

```
data(locarData)
```

Format

A time series of 1000 observations.

Source

H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Timsac78*. The Institute of Statistical Mathematics.

markov	<i>Maximum Likelihood Computation of Markovian Model</i>
--------	--

Description

Compute maximum likelihood estimates of Markovian model.

Usage

```
markov(y)
```

Arguments

y a multivariate time series.

Details

This function is usually used with [simcon](#).

Value

id	id[i]= 1 means that the i -th row of F contains free parameters.
ir	ir[i] denotes the position of the last non-zero element within the i -th row of F .
ij	ij[i] denotes the position of the i -th non-trivial row within F .
ik	ik[i] denotes the number of free parameters within the i -th non-trivial row of F .
grad	gradient vector.
matFi	initial estimate of the transition matrix F .
matF	transition matrix F .
matG	input matrix G .
davvar	DAVIDON variance.
arcoef	AR coefficient matrices. arcoef[i, j, k] shows the value of i -th row, j -th column, k -th order.
impulse	impulse response matrices.
macoef	MA coefficient matrices. macoef[i, j, k] shows the value of i -th row, j -th column, k -th order.
v	innovation variance.
aic	AIC.

References

H.Akaike, E.Arahata and T.Ozaki (1975) *Computer Science Monograph, No.5, Timsac74, A Time Series Analysis and Control Program Package (1)*. The Institute of Statistical Mathematics.

Examples

```
x <- matrix(rnorm(1000*2), nrow = 1000, ncol = 2)
ma <- array(0, dim = c(2,2,2))
ma[, , 1] <- matrix(c( -1.0,  0.0,
                    0.0, -1.0), nrow = 2, ncol = 2, byrow = TRUE)
ma[, , 2] <- matrix(c( -0.2,  0.0,
                    -0.1, -0.3), nrow = 2, ncol = 2, byrow = TRUE)
y <- mfilter(x, ma, "convolution")
ar <- array(0, dim = c(2,2,3))
ar[, , 1] <- matrix(c( -1.0,  0.0,
                    0.0, -1.0), nrow = 2, ncol = 2, byrow = TRUE)
ar[, , 2] <- matrix(c( -0.5, -0.2,
                    -0.2, -0.5), nrow = 2, ncol = 2, byrow = TRUE)
ar[, , 3] <- matrix(c( -0.3, -0.05,
                    -0.1, -0.30), nrow = 2, ncol = 2, byrow = TRUE)
z <- mfilter(y, ar, "recursive")
markov(z)
```

mfilter *Linear Filtering on a Multivariate Time Series*

Description

Applies linear filtering to a multivariate time series.

Usage

```
mfilter(x, filter, method = c("convolution", "recursive"), init)
```

Arguments

x a multivariate (m -dimensional, n length) time series $x[n, m]$.

filter an array of filter coefficients. `filter[i, j, k]` shows the value of i -th row, j -th column, k -th order

method either "convolution" or "recursive" (and can be abbreviated). If "convolution" a moving average is used: if "recursive" an autoregression is used. For convolution filters, the filter coefficients are for past value only.

init specifies the initial values of the time series just prior to the start value, in reverse time order. The default is a set of zeros.

Details

This is a multivariate version of "filter" function. Missing values are allowed in 'x' but not in 'filter' (where they would lead to missing values everywhere in the output). Note that there is an implied coefficient 1 at lag 0 in the recursive filter, which gives

$$y[i,]' = x[i,]' + f[, 1] \times y[i - 1,]' + \dots + f[, p] \times y[i - p,]'$$

No check is made to see if recursive filter is invertible: the output may diverge if it is not. The convolution filter is

$$y[i,]' = f[, 1] \times x[i,]' + \dots + f[, p] \times x[i - p + 1,]'$$

Value

mfilter returns a time series object.

Note

'convolve(, type="filter")' uses the FFT for computations and so may be faster for long filters on univariate time series (and so the time alignment is unclear), nor does it handle missing values. 'filter' is faster for a filter of length 100 on a series 1000, for examples.

See Also

[convolve](#), [arima.sim](#)

Examples

```

#AR model simulation
ar <- array(0, dim = c(3,3,2))
ar[, , 1] <- matrix(c(0.4, 0, 0.3,
                    0.2, -0.1, -0.5,
                    0.3, 0.1, 0), nrow = 3, ncol = 3, byrow = TRUE)
ar[, , 2] <- matrix(c(0, -0.3, 0.5,
                    0.7, -0.4, 1,
                    0, -0.5, 0.3), nrow = 3, ncol = 3, byrow = TRUE)
x <- matrix(rnorm(100*3), nrow = 100, ncol = 3)
y <- mfilter(x, ar, "recursive")

#Back to white noise
ma <- array(0, dim = c(3,3,3))
ma[, , 1] <- diag(3)
ma[, , 2] <- -ar[, , 1]
ma[, , 3] <- -ar[, , 2]
z <- mfilter(y, ma, "convolution")
mulcor(z)

#AR-MA model simulation
x <- matrix(rnorm(1000*2), nrow = 1000, ncol = 2)
ma <- array(0, dim = c(2,2,2))
ma[, , 1] <- matrix(c( -1.0, 0.0,
                    0.0, -1.0), nrow = 2, ncol = 2, byrow = TRUE)
ma[, , 2] <- matrix(c( -0.2, 0.0,
                    -0.1, -0.3), nrow = 2, ncol = 2, byrow = TRUE)
y <- mfilter(x, ma, "convolution")

ar <- array(0, dim = c(2,2,3))
ar[, , 1] <- matrix(c( -1.0, 0.0,
                    0.0, -1.0), nrow = 2, ncol = 2, byrow = TRUE)
ar[, , 2] <- matrix(c( -0.5, -0.2,
                    -0.2, -0.5), nrow = 2, ncol = 2, byrow = TRUE)
ar[, , 3] <- matrix(c( -0.3, -0.05,
                    -0.1, -0.30), nrow = 2, ncol = 2, byrow = TRUE)
z <- mfilter(y, ar, "recursive")

```

mlocar

Minimum AIC Method of Locally Stationary AR Model Fitting; Scalar Case

Description

Locally fit autoregressive models to non-stationary time series by minimum AIC procedure.

Usage

```
mlocar(y, max.order = NULL, span, const = 0, plot = TRUE)
```

Arguments

y	a univariate time series.
max.order	upper limit of the order of AR model. Default is $2\sqrt{n}$, where n is the length of the time series y .
span	length of the basic local span.
const	integer. 0 denotes constant vector is not included as a regressor and 1 denotes constant vector is included as the first regressor.
plot	logical. If TRUE (default), spectrums pspec are plotted.

Details

The data of length n are divided into k locally stationary spans,

$$| \langle \dots n_1 \dots \rangle | \langle \dots n_2 \dots \rangle | \langle \dots n_3 \dots \rangle | \dots | \langle \dots n_k \dots \rangle |$$

where n_i ($i = 1, \dots, k$) denotes the number of basic spans, each of length span, which constitute the i -th locally stationary span. At each local span, the process is represented by a stationary autoregressive model.

Value

mean	mean.
var	variance.
ns	the number of local spans.
order	order of the current model.
arcoef	AR coefficients of current model.
v	innovation variance of the current model.
init	initial point of the data fitted to the current model.
end	end point of the data fitted to the current model.
pspec	power spectrum.
npres	data length of the preceding stationary block.
nnew	data length of the new block.
order.mov	order of the moving model.
v.mov	innovation variance of the moving model.
aic.mov	AIC of the moving model.
order.const	order of the constant model.
v.const	innovation variance of the constant model.
aic.const	AIC of the constant model.

References

G.Kitagawa and H.Akaike (1978) A Procedure for The Modeling of Non-Stationary Time Series. Ann. Inst. Statist. Math., 30, B, 351–363.

H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Tim-sac78*. The Institute of Statistical Mathematics.

Examples

```
data(locarData)
z <- mlocar(locarData, max.order = 10, span = 300, const = 0)
z$arcoef
```

mlomar	<i>Minimum AIC Method of Locally Stationary Multivariate AR Model Fitting</i>
--------	---

Description

Locally fit multivariate autoregressive models to non-stationary time series by the minimum AIC procedure using the householder transformation.

Usage

```
mlocar(y, max.order = NULL, span, const = 0)
```

Arguments

y	a multivariate time series.
max.order	upper limit of the order of AR model, less than or equal to $n/2d$ where n is the length and d is the dimension of the time series y . Default is $\min(2\sqrt{n}, n/2d)$.
span	length of basic local span. Let m denote max.order, if $n - m - 1$ is less than or equal to span or $n - m - 1 - \text{span}$ is less than $2md + \text{const}$, span is $n - m$.
const	integer. '0' denotes constant vector is not included as a regressor and '1' denotes constant vector is included as the first regressor.

Details

The data of length n are divided into k locally stationary spans,

$$| \langle \dots n_1 \dots \rangle | \langle \dots n_2 \dots \rangle | \langle \dots n_3 \dots \rangle | \dots | \langle \dots n_k \dots \rangle |$$

where n_i ($i = 1, \dots, k$) denoted the number of basic spans, each of length span, which constitute the i -th locally stationary span. At each local span, the process is represented by a stationary autoregressive model.

Value

mean	mean.
var	variance.
ns	the number of local spans.
order	order of the current model.
aic	AIC of the current model.
arcoef	AR coefficient matrices of the current model. <code>arcoef[[m]][i,j,k]</code> shows the value of i -th row, j -th column, k -th order of m -th model.
v	innovation variance of the current model.
init	initial point of the data fitted to the current model.
end	end point of the data fitted to the current model.
npre	data length of the preceding stationary block.
nnew	data length of the new block.
order.mov	order of the moving model.
aic.mov	AIC of the moving model.
order.const	order of the constant model.
aic.const	AIC of the constant model.

References

- G.Kitagawa and H.Akaike (1978) A Procedure for The Modeling of Non-Stationary Time Series. *Ann. Inst. Statist. Math.*, 30, B, 351–363.
- H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Tim-sac78*. The Institute of Statistical Mathematics.

Examples

```
data(Amerikamaru)
mlomar(Amerikamaru, max.order = 10, span = 300, const = 0)
```

mulbar

Multivariate Bayesian Method of AR Model Fitting

Description

Determine multivariate autoregressive models by a Bayesian procedure. The basic least squares estimates of the parameters are obtained by the householder transformation.

Usage

```
mulbar(y, max.order = NULL, plot = FALSE)
```

Arguments

<code>y</code>	a multivariate time series.
<code>max.order</code>	upper limit of the order of AR model, less than or equal to $n/2d$ where n is the length and d is the dimension of the time series y . Default is $\min(2\sqrt{n}, n/2d)$.
<code>plot</code>	logical. If TRUE, <code>daic</code> is plotted.

Details

The statistic AIC is defined by

$$AIC = n \log(\det(v)) + 2k,$$

where n is the number of data, v is the estimate of innovation variance matrix, \det is the determinant and k is the number of free parameters.

Bayesian weight of the m -th order model is defined by

$$W(m) = \text{const} \times \frac{C(m)}{m+1},$$

where const is the normalizing constant and $C(m) = \exp(-0.5AIC(m))$. The Bayesian estimates of partial autoregression coefficient matrices of forward and backward models are obtained by ($m = 1, \dots, \text{lag}$)

$$G(m) = G(m)D(m),$$

$$H(m) = H(m)D(m),$$

where the original $G(m)$ and $H(m)$ are the (conditional) maximum likelihood estimates of the highest order coefficient matrices of forward and backward AR models of order m and $D(m)$ is defined by

$$D(m) = W(m) + \dots + W(\text{lag}).$$

The equivalent number of parameters for the Bayesian model is defined by

$$ek = \{D(1)^2 + \dots + D(\text{lag})^2\}id + \frac{id(id+1)}{2}$$

where id denotes dimension of the process.

Value

<code>mean</code>	mean.
<code>var</code>	variance.
<code>v</code>	innovation variance.
<code>aic</code>	AIC.
<code>aicmin</code>	minimum AIC.
<code>daic</code>	AIC-aicmin.
<code>order.maice</code>	order of minimum AIC.
<code>v.maice</code>	MAICE innovation variance.

bweight	Bayesian weights.
integra.bweight	integrated Bayesian Weights.
arcoef.for	AR coefficients (forward model). arcoef.for[i, j, k] shows the value of i -th row, j -th column, k -th order.
arcoef.back	AR coefficients (backward model). arcoef.back[i, j, k] shows the value of i -th row, j -th column, k -th order.
pacoef.for	partial autoregression coefficients (forward model).
pacoef.back	partial autoregression coefficients (backward model).
v.bay	innovation variance of the Bayesian model.
aic.bay	equivalent AIC of the Bayesian (forward) model.

References

- H.Akaike (1978) A Bayesian Extension of The Minimum AIC Procedure of Autoregressive Model Fitting. Research Memo. NO.126, The Institute of Statistical Mathematics.
- G.Kitagawa and H.Akaike (1978) A Procedure for The Modeling of Non-stationary Time Series. Ann. Inst. Statist. Math., 30, B, 351–363.
- H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Tim-sac78*. The Institute of Statistical Mathematics.

Examples

```
data(Powerplant)
z <- mulbar(Powerplant, max.order = 10)
z$pacoef.for
z$pacoef.back
```

mulcor

Multiple Correlation

Description

Estimate multiple correlation.

Usage

```
mulcor(y, lag = NULL, plot = TRUE, lag_axis = TRUE)
```

Arguments

y	a multivariate time series.
lag	maximum lag. Default is $2\sqrt{n}$, where n is the length of the time series y .
plot	logical. If TRUE (default), correlations cor are plotted.
lag_axis	logical. If TRUE (default) with plot=TRUE, x -axis is drawn.

Value

cov	covariances.
cor	correlations (normalized covariances).
mean	mean.

References

H.Akaike and T.Nakagawa (1988) *Statistical Analysis and Control of Dynamic Systems*. Kluwer Academic publishers.

Examples

```
# Example 1
y <- rnorm(1000)
dim(y) <- c(500,2)
mulcor(y, lag_axis = FALSE)

# Example 2
xorg <- rnorm(1003)
x <- matrix(0, nrow = 1000, ncol = 2)
x[, 1] <- xorg[1:1000]
x[, 2] <- xorg[4:1003] + 0.5*rnorm(1000)
mulcor(x, lag = 20)
```

mulfrf

Frequency Response Function (Multiple Channel)

Description

Compute multiple frequency response function, gain, phase, multiple coherency, partial coherency and relative error statistics.

Usage

```
mulfrf(y, lag = NULL, iovar = NULL)
```

Arguments

y	a multivariate time series.
lag	maximum lag. Default is $2\sqrt{n}$, where n is the number of rows in y .
iovar	input variables $\text{iovar}[i]$ ($i = 1, k$) and output variable $\text{iovar}[k+1]$ ($1 \leq k \leq d$), where d is the number of columns in y . Default is $c(1 : d)$.

Value

cospec	spectrum (complex).
freqr	frequency response function : real part.
freqi	frequency response function : imaginary part.
gain	gain.
phase	phase.
pcoh	partial coherency.
errstat	relative error statistics.
mcoh	multiple coherency.

References

H.Akaike and T.Nakagawa (1988) *Statistical Analysis and Control of Dynamic Systems*. Kluwer Academic publishers.

Examples

```
ar <- array(0, dim = c(3,3,2))
ar[, , 1] <- matrix(c(0.4, 0, 0.3,
                    0.2, -0.1, -0.5,
                    0.3, 0.1, 0), nrow = 3, ncol = 3, byrow = TRUE)
ar[, , 2] <- matrix(c(0, -0.3, 0.5,
                    0.7, -0.4, 1,
                    0, -0.5, 0.3), nrow = 3, ncol = 3, byrow = TRUE)
x <- matrix(rnorm(200*3), nrow = 200, ncol = 3)
y <- mfilter(x, ar, "recursive")
mulfrf(y, lag = 20)
```

mulmar

*Multivariate Case of Minimum AIC Method of AR Model Fitting***Description**

Fit a multivariate autoregressive model by the minimum AIC procedure. Only the possibilities of zero coefficients at the beginning and end of the model are considered. The least squares estimates of the parameters are obtained by the householder transformation.

Usage

```
mulmar(y, max.order = NULL, plot = FALSE)
```

Arguments

y	a multivariate time series.
max.order	upper limit of the order of AR model, less than or equal to $n/2d$ where n is the length and d is the dimension of the time series y . Default is $\min(2\sqrt{n}, n/2d)$.
plot	logical. If TRUE, <code>daic[[1]]</code> , <code>...</code> , <code>daic[[d]]</code> are plotted.

Details

Multivariate autoregressive model is defined by

$$y(t) = A(1)y(t-1) + A(2)y(t-2) + \dots + A(p)y(t-p) + u(t),$$

where p is order of the model and $u(t)$ is Gaussian white noise with mean 0 and variance matrix matv . AIC is defined by

$$AIC = n \log(\det(v)) + 2k,$$

where n is the number of data, v is the estimate of innovation variance matrix, \det is the determinant and k is the number of free parameters.

Value

mean	mean.
var	variance.
v	innovation variance.
aic	AIC.
aicmin	minimum AIC.
daic	AIC-aicmin.
order.maice	order of minimum AIC.
v.maice	MAICE innovation variance.
np	number of parameters.
jnd	specification of i -th regressor.
subregcoef	subset regression coefficients.
rvar	residual variance.
aicf	final estimate of AIC ($= n \log(\text{rvar}) + 2np$).
respns	instantaneous response.
regcoef	regression coefficients matrix.
matv	innovation variance matrix.
morder	order of the MAICE model.
arcoef	AR coefficients. <code>arcoef[i, j, k]</code> shows the value of i -th row, j -th column, k -th order.
aicsum	the sum of aicf.

References

- G.Kitagawa and H.Akaike (1978) A Procedure for The Modeling of Non-stationary Time Series. *Ann. Inst. Statist. Math.*, 30, B, 351–363.
- H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Tim-sac78*. The Institute of Statistical Mathematics.

Examples

```

# Example 1
data(Powerplant)
z <- mulmar(Powerplant, max.order = 10)
z$arcoef

# Example 2
ar <- array(0, dim = c(3,3,2))
ar[, , 1] <- matrix(c(0.4, 0, 0.3,
                    0.2, -0.1, -0.5,
                    0.3, 0.1, 0), nrow = 3, ncol = 3, byrow = TRUE)
ar[, , 2] <- matrix(c(0, -0.3, 0.5,
                    0.7, -0.4, 1,
                    0, -0.5, 0.3), nrow = 3, ncol = 3, byrow = TRUE)
x <- matrix(rnorm(200*3), nrow = 200, ncol = 3)
y <- mfilter(x, ar, "recursive")
z <- mulmar(y, max.order = 10)
z$arcoef

```

mulnos

*Relative Power Contribution***Description**

Compute relative power contributions in differential and integrated form, assuming the orthogonality between noise sources.

Usage

```
mulnos(y, max.order = NULL, control = NULL, manip = NULL, h)
```

Arguments

<code>y</code>	a multivariate time series.
<code>max.order</code>	upper limit of model order. Default is $2\sqrt{n}$, where n is the length of time series y .
<code>control</code>	controlled variables. Default is $c(1 : d)$, where d is the dimension of the time series y .
<code>manip</code>	manipulated variables. Default number of manipulated variable is '0'.
<code>h</code>	specify frequencies $i/2h$ ($i = 0, \dots, h$).

Value

<code>nperr</code>	a normalized prediction error covariance matrix.
<code>diffrr</code>	differential relative power contribution.
<code>integr</code>	integrated relative power contribution.

References

H.Akaike and T.Nakagawa (1988) *Statistical Analysis and Control of Dynamic Systems*. Kluwer Academic publishers.

Examples

```
ar <- array(0, dim = c(3,3,2))
ar[, , 1] <- matrix(c(0.4, 0, 0.3,
                    0.2, -0.1, -0.5,
                    0.3, 0.1, 0), nrow = 3, ncol = 3, byrow = TRUE)
ar[, , 2] <- matrix(c(0, -0.3, 0.5,
                    0.7, -0.4, 1,
                    0, -0.5, 0.3), nrow = 3, ncol = 3, byrow = TRUE)
x <- matrix(rnorm(200*3), nrow = 200, ncol = 3)
y <- mfilter(x, ar, "recursive")
mulnos(y, max.order = 10, h = 20)
```

mulrsp

Multiple Rational Spectrum

Description

Compute rational spectrum for d-dimensional ARMA process.

Usage

```
mulrsp(h, d, cov, ar = NULL, ma = NULL, log = FALSE, plot = TRUE, ...)
```

Arguments

h	specify frequencies $i/2h$ ($i = 0, 1, \dots, h$).
d	dimension of the observation vector.
cov	covariance matrix.
ar	coefficient matrix of autoregressive model. ar[i, j, k] shows the value of i -th row, j -th column, k -th order.
ma	coefficient matrix of moving average model. ma[i, j, k] shows the value of i -th row, j -th column, k -th order.
log	logical. If TRUE, rational spectrums rspec are plotted as $\log(\text{rspec})$.
plot	logical. If TRUE, rational spectrums rspec are plotted.
...	graphical arguments passed to plot.specmx .

Details

ARMA process :

$$y(t) - A(1)y(t-1) - \dots - A(p)y(t-p) = u(t) - B(1)u(t-1) - \dots - B(q)u(t-q)$$

where $u(t)$ is a white noise with zero mean vector and covariance matrix cov.

Value

rspec rational spectrum. An object of class "specmx".
 scoh simple coherence.

References

H.Akaike and T.Nakagawa (1988) *Statistical Analysis and Control of Dynamic Systems*. Kluwer Academic publishers.

Examples

```
# Example 1 for the normal distribution
xorg <- rnorm(1003)
x <- matrix(0, nrow = 1000, ncol = 2)
x[, 1] <- xorg[1:1000]
x[, 2] <- xorg[4:1003] + 0.5*rnorm(1000)
aaa <- ar(x)
mulrsp(h = 20, d = 2, cov = aaa$var.pred, ar = aaa$ar)

# Example 2 for the AR model
ar <- array(0, dim = c(3,3,2))
ar[, , 1] <- matrix(c(0.4, 0, 0.3,
                    0.2, -0.1, -0.5,
                    0.3, 0.1, 0), nrow = 3, ncol = 3, byrow = TRUE)
ar[, , 2] <- matrix(c(0, -0.3, 0.5,
                    0.7, -0.4, 1,
                    0, -0.5, 0.3), nrow = 3, ncol = 3, byrow = TRUE)
x <- matrix(rnorm(200*3), nrow = 200, ncol = 3)
y <- mfilter(x, ar, "recursive")
z <- fpec(y, max.order = 10)
mulrsp(h = 20, d = 3, cov = z$perr, ar = z$arcoef)
```

 mulspe

Multiple Spectrum

Description

Compute multiple spectrum estimates using Akaike window or Hanning window.

Usage

```
mulspe(y, lag = NULL, window = "Akaike", plot = TRUE, ...)
```

Arguments

y a multivariate time series with d variables and n observations.
 lag maximum lag. Default is $2\sqrt{n}$, where n is the number of observations.

window	character string giving the definition of smoothing window. Allowed strings are "Akaike" (default) or "Hanning".
plot	logical. If TRUE (default) spectrums are plotted as (d, d) matrix.
	Diagonal parts : Auto spectrums for each series.
	Lower triangular parts : Amplitude spectrums.
	Upper triangular part : Phase spectrums.
...	graphical arguments passed to <code>plot.specmx</code> .

Details

Hanning Window : $a_1(0)=0.5, a_1(1)=a_1(-1)=0.25, a_1(2)=a_1(-2)=0$
 Akaike Window : $a_2(0)=0.625, a_2(1)=a_2(-1)=0.25, a_2(2)=a_2(-2)=-0.0625$

Value

spec	spectrum smoothing by 'window'.
specmx	spectrum matrix. An object of class "specmx".
	On and lower diagonal : Real parts
	Upper diagonal : Imaginary parts
stat	test statistics.
coh	simple coherence by 'window'.

References

H.Akaike and T.Nakagawa (1988) *Statistical Analysis and Control of Dynamic Systems*. Kluwer Academic publishers.

Examples

```
sgn1 <- rnorm(1003)
x <- matrix(0, nrow = 1000, ncol = 2)
x[, 1] <- sgn1[4:1003]
# x[i,2] = 0.9*x[i-3,1] + 0.2*N(0,1)
x[, 2] <- 0.9*sgn1[1:1000] + 0.2*rnorm(1000)
mulspe(x, lag = 100, window = "Hanning")
```

 nonst

Non-stationary Power Spectrum Analysis

Description

Locally fit autoregressive models to non-stationary time series by AIC criterion.

Usage

```
nonst(y, span, max.order = NULL, plot = TRUE)
```

Arguments

<code>y</code>	a univariate time series.
<code>span</code>	length of the basic local span.
<code>max.order</code>	highest order of AR model. Default is $2\sqrt{n}$, where n is the length of the time series y .
<code>plot</code>	logical. If TRUE (the default), spectrums are plotted.

Details

The basic AR model is given by

$$y(t) = A(1)y(t-1) + A(2)y(t-2) + \dots + A(p)y(t-p) + u(t),$$

where p is order of the AR model and $u(t)$ is innovation variance. AIC is defined by

$$AIC = n \log(\det(sd)) + 2k,$$

where n is the length of data, sd is the estimates of the innovation variance and k is the number of parameter.

Value

<code>ns</code>	the number of local spans.
<code>arcoef</code>	AR coefficients.
<code>v</code>	innovation variance.
<code>aic</code>	AIC.
<code>daic21</code>	= AIC2 - AIC1.
<code>daic</code>	= daic21/ n (n is the length of the current model).
<code>init</code>	start point of the data fitted to the current model.
<code>end</code>	end point of the data fitted to the current model.
<code>pspec</code>	power spectrum.

References

H.Akaike, E.Arahata and T.Ozaki (1976) *Computer Science Monograph, No.6, Timsac74 A Time Series Analysis and Control Program Package (2)*. The Institute of Statistical Mathematics.

Examples

```
# Non-stationary Test Data
data(nonstData)
nonst(nonstData, span = 700, max.order = 49)
```

nonstData	<i>Non-stationary Test Data</i>
-----------	---------------------------------

Description

A non-stationary data for testing [nonst](#).

Usage

```
data(nonstData)
```

Format

A time series of 2100 observations.

Source

H.Akaike, E.Arahata and T.Ozaki (1976) *Computer Science Monograph, No.6, Timsac74 A Time Series Analysis and Control Program Package (2)*. The Institute of Statistical Mathematics.

optdes	<i>Optimal Controller Design</i>
--------	----------------------------------

Description

Compute optimal controller gain matrix for a quadratic criterion defined by two positive definite matrices Q and R.

Usage

```
optdes(y, max.order = NULL, ns, q, r)
```

Arguments

y	a multivariate time series.
max.order	upper limit of model order. Default is $2\sqrt{n}$, where n is the length of the time series y .
ns	number of D.P. stages.
q	positive definite (m, m) matrix Q , where m is the number of controlled variables. A quadratic criterion is defined by Q and R .
r	positive definite (l, l) matrix R , where l is the number of manipulated variables.

Value

perr	prediction error covariance matrix.
trans	first m columns of transition matrix, where m is the number of controlled variables.
gamma	gamma matrix.
gain	gain matrix.

References

H.Akaike and T.Nakagawa (1988) *Statistical Analysis and Control of Dynamic Systems*. Kluwer Academic publishers.

Examples

```
# Multivariate Example Data
ar <- array(0, dim = c(3,3,2))
ar[, , 1] <- matrix(c(0.4, 0, 0.3,
                    0.2, -0.1, -0.5,
                    0.3, 0.1, 0), nrow= 3, ncol= 3, byrow = TRUE)
ar[, , 2] <- matrix(c(0, -0.3, 0.5,
                    0.7, -0.4, 1,
                    0, -0.5, 0.3), nrow= 3, ncol= 3, byrow = TRUE)
x <- matrix(rnorm(200*3), nrow = 200, ncol = 3)
y <- mfilter(x, ar, "recursive")
q.mat <- matrix(c(0.16,0,0,0.09), nrow = 2, ncol = 2)
r.mat <- as.matrix(0.001)
optdes(y, ns = 20, q = q.mat, r = r.mat)
```

Description

Perform optimal control simulation and evaluate the means and variances of the controlled and manipulated variables X and Y .

Usage

```
optim(y, max.order = NULL, ns, q, r, noise = NULL, len, plot = TRUE)
```

Arguments

y	a multivariate time series.
max.order	upper limit of model order. Default is $2\sqrt{n}$, where n is the length of the time series y .
ns	number of steps of simulation.
q	positive definite matrix Q .
r	positive definite matrix R .
noise	noise. If not provided, Gaussian vector white noise with the length len is generated.
len	length of white noise record.
plot	logical. If TRUE (default), controlled variables X and manipulated variables Y are plotted.

Value

trans	first m columns of transition matrix, where m is the number of controlled variables.
gamma	gamma matrix.
gain	gain matrix.
convar	controlled variables X .
manvar	manipulated variables Y .
xmean	mean of X .
ymean	mean of Y .
xvar	variance of X .
yvar	variance of Y .
x2sum	sum of X^2 .
y2sum	sum of Y^2 .
x2mean	mean of X^2 .
y2mean	mean of Y^2 .

References

H.Akaike and T.Nakagawa (1988) *Statistical Analysis and Control of Dynamic Systems*. Kluwer Academic publishers.

Examples

```
# Multivariate Example Data
ar <- array(0, dim = c(3,3,2))
ar[, , 1] <- matrix(c(0.4, 0, 0.3,
                    0.2, -0.1, -0.5,
                    0.3, 0.1, 0), nrow = 3, ncol = 3, byrow = TRUE)
ar[, , 2] <- matrix(c(0, -0.3, 0.5,
                    0.7, -0.4, 1,
                    0, -0.5, 0.3), nrow = 3, ncol = 3, byrow = TRUE)
x <- matrix(rnorm(200*3), nrow = 200, ncol = 3)
y <- mfilter(x, ar, "recursive")
q.mat <- matrix(c(0.16,0,0,0.09), nrow = 2, ncol = 2)
r.mat <- as.matrix(0.001)
optsim(y, max.order = 10, ns = 20, q = q.mat, r = r.mat, len = 20)
```

perars

Periodic Autoregression for a Scalar Time Series

Description

This is the program for the fitting of periodic autoregressive models by the method of least squares realized through householder transformation.

Usage

```
perars(y, ni, lag = NULL, ksw = 0)
```

Arguments

y	a univariate time series.
ni	number of instants in one period.
lag	maximum lag of periods. Default is $2\sqrt{ni}$.
ksw	integer. '0' denotes constant vector is not included as a regressor and '1' denotes constant vector is included as the first regressor.

Details

Periodic autoregressive model ($i = 1, \dots, nd, j = 1, \dots, ni$) is defined by

$$z(i, j) = y(ni(i-1) + j),$$

$$z(i, j) = c(j) + A(1, j, 0)z(i, 1) + \dots + A(j-1, j, 0)z(i, j-1) + A(1, j, 1)z(i-1, 1) + \dots + A(ni, j, 1)z(i-1, ni) + \dots + u(i, j),$$

where nd is the number of periods, ni is the number of instants in one period and $u(i, j)$ is the Gaussian white noise. When ksw is set to '0', the constant term $c(j)$ is excluded.

The statistics AIC is defined by $AIC = n \log(\det(v)) + 2k$, where n is the length of data, v is the estimate of the innovation variance matrix and k is the number of parameters. The outputs are the estimates of the regression coefficients and innovation variance of the periodic AR model for each instant.

Value

mean	mean.
var	variance.
subset	specification of i -th regressor ($i = 1, \dots, ni$).
regcoef	regression coefficients.
rvar	residual variances.
np	number of parameters.
aic	AIC.
v	innovation variance matrix.
arcoef	AR coefficient matrices. arcoef[i, k] shows i -th regressand of k -th period former.
const	constant vector.
morder	order of the MAICE model.

References

- M.Pagano (1978) On Periodic and Multiple Autoregressions. *Ann. Statist.*, 6, 1310–1317.
- H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Tim-sac78*. The Institute of Statistical Mathematics.

Examples

```
data(Airpollution)
perars(Airpollution, ni = 6, lag = 2, ksw = 1)
```

plot.decomp

Plot Trend, Seasonal, AR Components and Trading Day Factor

Description

Plot trend component, seasonal component, AR component, noise and trading day factor returned by [decomp](#).

Usage

```
## S3 method for class 'decomp'
plot(x, ...)
```

Arguments

`x` an object of class "decomp".

`...` further graphical parameters may also be supplied as arguments.

plot.specmx	<i>Plot Spectrum</i>
-------------	----------------------

Description

Plot spectrum returned by `mulspe` and `mulrsp`. On and lower diagonal are real parts, and upper diagonal are imaginary parts.

Usage

```
## S3 method for class 'specmx'
plot(x, plot.scale = TRUE, ...)
```

Arguments

<code>x</code>	An object of class "specmx".
<code>plot.scale</code>	logical. IF TRUE, the common range of the <i>y</i> -axis is used.
<code>...</code>	further graphical parameters may also be supplied as arguments.

Powerplant	<i>Power Plant Data</i>
------------	-------------------------

Description

A Power plant data for testing `mulbar` and `mulmar`.

Usage

```
data(Powerplant)
```

Format

A 2-dimensional array with 500 observations on 3 variables.

[, 1]	command
[, 2]	temperature
[, 3]	fuel

Source

H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Tim-sac78*. The Institute of Statistical Mathematics.

prctr *Prediction Program*

Description

Operate on a real record of a vector process and compute predicted values.

Usage

```
prctr(y, r, s, h, arcoef, macoef = NULL, impulse = NULL, v, plot = TRUE)
```

Arguments

y	a univariate time series or a multivariate time series.
r	one step ahead prediction starting position R .
s	long range forecast starting position S .
h	maximum span of long range forecast H .
arcoef	AR coefficient matrices.
macoef	MA coefficient matrices.
impulse	impulse response matrices.
v	innovation variance.
plot	logical. If TRUE (default), the real data and predicted values are plotted.

Details

One step ahead Prediction starts at time R and ends at time S . Prediction is continued without new observations until time $S + H$. Basic model is the autoregressive moving average model of $y(t)$ which is given by

$$y(t) - A(t)y(t-1) - \dots - A(p)y(t-p) = u(t) - B(1)u(t-1) - \dots - B(q)u(t-q),$$

where p is AR order and q is MA order.

Value

predct	predicted values : predct[i] ($r \leq i \leq s+h$).
ys	predct[i] - y[i] ($r \leq i \leq n$).
pstd	predct[i] + (standard deviation) ($s \leq i \leq s+h$).
p2std	predct[i] + 2*(standard deviation) ($s \leq i \leq s+h$).
p3std	predct[i] + 3*(standard deviation) ($s \leq i \leq s+h$).
mstd	predct[i] - (standard deviation) ($s \leq i \leq s+h$).
m2std	predct[i] - 2*(standard deviation) ($s \leq i \leq s+h$).
m3std	predct[i] - 3*(standard deviation) ($s \leq i \leq s+h$).

References

H.Akaike, E.Arahata and T.Ozaki (1975) *Computer Science Monograph, No.6, Timsac74, A Time Series Analysis and Control Program Package (2)*. The Institute of Statistical Mathematics.

Examples

```
# "arima.sim" is a function in "stats".
# Note that the sign of MA coefficient is opposite from that in "timsac".
y <- arima.sim(list(order=c(2,0,1), ar=c(0.64,-0.8), ma=c(-0.5)), n = 1000)
y1 <- y[1:900]
z <- autoarmafit(y1)
ar <- z$model[[1]]$arcoef
ma <- z$model[[1]]$macoef
var <- z$model[[1]]$v
y2 <- y[901:990]
prdctr(y2, r = 50, s = 90, h = 10, arcoef = ar, macoef = ma, v = var)
```

 raspec

Rational Spectrum

Description

Compute power spectrum of ARMA process.

Usage

```
raspec(h, var, arcoef = NULL, macoef = NULL, log = FALSE, plot = TRUE)
```

Arguments

h	specify frequencies $i/2h$ ($i = 0, 1, \dots, h$).
var	variance.
arcoef	AR coefficients.
macoef	MA coefficients.
log	logical. If TRUE, the spectrum is plotted as $\log(\text{raspec})$.
plot	logical. If TRUE (default), the spectrum is plotted.

Details

ARMA process :

$$y(t) - a(1)y(t-1) - \dots - a(p)y(t-p) = u(t) - b(1)u(t-1) - \dots - b(q)u(t-q)$$

where p is AR order, q is MA order and $u(t)$ is a white noise with zero mean and variance equal to var.

Value

raspec gives the rational spectrum.

References

H.Akaike and T.Nakagawa (1988) *Statistical Analysis and Control of Dynamic Systems*. Kluwer Academic publishers.

Examples

```
# Example 1 for the AR model
raspec(h = 100, var = 1, arcoef = c(0.64,-0.8))

# Example 2 for the MA model
raspec(h = 20, var = 1, macoef = c(0.64,-0.8))
```

sglfr

Frequency Response Function (Single Channel)

Description

Compute 1-input,1-output frequency response function, gain, phase, coherency and relative error statistics.

Usage

```
sglfr(y, lag = NULL, invar, outvar)
```

Arguments

y	a multivariate time series.
lag	maximum lag. Default $2\sqrt{n}$, where n is the length of the time series y .
invar	within d variables of the spectrum, invar-th variable is taken as an input variable.
outvar	within d variables of the spectrum, outvar-th variable is taken as an output variable .

Value

inspec	power spectrum (input).
outspec	power spectrum (output).
cspec	co-spectrum.
qspec	quad-spectrum.
gain	gain.
coh	coherency.

freqr	frequency response function : real part.
freqi	frequency response function : imaginary part.
errstat	relative error statistics.
phase	phase.

References

H.Akaike and T.Nakagawa (1988) *Statistical Analysis and Control of Dynamic Systems*. Kluwer Academic publishers.

Examples

```
ar <- array(0, dim = c(3,3,2))
ar[, , 1] <- matrix(c(0.4, 0, 0.3,
                    0.2, -0.1, -0.5,
                    0.3, 0.1, 0), nrow = 3, ncol = 3, byrow = TRUE)
ar[, , 2] <- matrix(c(0, -0.3, 0.5,
                    0.7, -0.4, 1,
                    0, -0.5, 0.3), nrow = 3, ncol = 3, byrow = TRUE)
x <- matrix(rnorm(200*3), nrow = 200, ncol = 3)
y <- mfilter(x, ar, "recursive")
sglfr(y, lag = 20, invar = 1, outvar = 2)
```

 simcon

Optimal Controller Design and Simulation

Description

Produce optimal controller gain and simulate the controlled process.

Usage

```
simcon(span, len, r, arcoef, impulse, v, weight)
```

Arguments

span	span of control performance evaluation.
len	length of experimental observation.
r	dimension of control input, less than or equal to d (dimension of a vector).
arcoef	matrices of autoregressive coefficients. <code>arcoef[i, j, k]</code> shows the value of i -th row, j -th column, k -th order.
impulse	impulse response matrices.
v	covariance matrix of innovation.
weight	weighting matrix of performance.

Details

The basic state space model is obtained from the autoregressive moving average model of a vector process $y(t)$;

$$y(t) - A(1)y(t-1) - \dots - A(p)y(t-p) = u(t) - B(1)u(t-1) - \dots - B(p-1)u(t-p+1),$$

where $A(i)$ ($i = 1, \dots, p$) are the autoregressive coefficients of the ARMA representation of $y(t)$.

Value

gain	controller gain.
ave	average value of i -th component of y .
var	variance.
std	standard deviation.
bc	sub matrices (pd, r) of impulse response matrices, where p is the order of the process, d is the dimension of the vector and r is the dimension of the control input.
bd	sub matrices $(pd, d - r)$ of impulse response matrices.

References

H.Akaike, E.Arahata and T.Ozaki (1975) *Computer Science Monograph, No.6, Timsac74, A Time Series Analysis and Control Program Package (2)*. The Institute of Statistical Mathematics.

Examples

```
x <- matrix(rnorm(1000*2), nrow = 1000, ncol = 2)
ma <- array(0, dim = c(2,2,2))
ma[, , 1] <- matrix(c( -1.0,  0.0,
                    0.0, -1.0), nrow = 2, ncol = 2, byrow = TRUE)
ma[, , 2] <- matrix(c( -0.2,  0.0,
                    -0.1, -0.3), nrow = 2, ncol = 2, byrow = TRUE)
y <- mfilter(x, ma, "convolution")

ar <- array(0, dim = c(2,2,3))
ar[, , 1] <- matrix(c( -1.0,  0.0,
                    0.0, -1.0), nrow = 2, ncol = 2, byrow = TRUE)
ar[, , 2] <- matrix(c( -0.5, -0.2,
                    -0.2, -0.5), nrow = 2, ncol = 2, byrow = TRUE)
ar[, , 3] <- matrix(c( -0.3, -0.05,
                    -0.1, -0.3), nrow = 2, ncol = 2, byrow = TRUE)
y <- mfilter(y, ar, "recursive")

z <- markov(y)
weight <- matrix(c(0.0002,  0.0,
                  0.0,    2.9 ), nrow = 2, ncol = 2, byrow = TRUE)
simcon(span = 50, len = 700, r = 1, z$arcoef, z$impulse, z$v, weight)
```

thirmo	<i>Third Order Moments</i>
--------	----------------------------

Description

Compute the third order moments.

Usage

```
thirmo(y, lag = NULL, plot = TRUE)
```

Arguments

y	a univariate time series.
lag	maximum lag. Default is $2\sqrt{n}$, where n is the length of the time series y .
plot	logical. If TRUE (default), autocovariance acor is plotted.

Value

mean	mean.
acov	autocovariance.
acor	normalized covariance.
tmomnt	third order moments.

References

H.Akaike, E.Arahata and T.Ozaki (1975) *Computer Science Monograph, No.6, Timsac74, A Time Series Analysis and Control Program Package (2)*. The Institute of Statistical Mathematics.

Examples

```
data(bispecData)
z <- thirmo(bispecData, lag = 30)
z$tmomnt
```

 unibar

 Univariate Bayesian Method of AR Model Fitting

Description

This program fits an autoregressive model by a Bayesian procedure. The least squares estimates of the parameters are obtained by the householder transformation.

Usage

```
unibar(y, ar.order = NULL, plot = TRUE)
```

Arguments

y	a univariate time series.
ar.order	order of the AR model. Default is $2\sqrt{n}$, where n is the length of the time series y .
plot	logical. If TRUE (default), daic, pacoef and pspec are plotted.

Details

The AR model is given by

$$y(t) = a(1)y(t-1) + \dots + a(p)y(t-p) + u(t),$$

where p is AR order and $u(t)$ is Gaussian white noise with mean 0 and variance $v(p)$. The basic statistic AIC is defined by

$$AIC = n \log(\det(v)) + 2m,$$

where n is the length of data, v is the estimate of innovation variance, and m is the order of the model.

Bayesian weight of the m -th order model is defined by

$$W(m) = CONST \times \frac{C(m)}{m+1},$$

where $CONST$ is the normalizing constant and $C(m) = \exp(-0.5AIC(m))$. The equivalent number of free parameter for the Bayesian model is defined by

$$ek = D(1)^2 + \dots + D(k)^2 + 1,$$

where $D(j)$ is defined by $D(j) = W(j) + \dots + W(k)$. m in the definition of AIC is replaced by ek to be define an equivalent AIC for a Bayesian model.

Value

mean	mean.
var	variance.
v	innovation variance.
aic	AIC.
aicmin	minimum AIC.
daic	AIC-aicmin.
order.maice	order of minimum AIC.
v.maice	innovation variance attained at m=order.maice.
pacoef	partial autocorrelation coefficients (least squares estimate).
bweight	Bayesian Weight.
integra.bweight	integrated Bayesian weights.
v.bay	innovation variance of Bayesian model.
aic.bay	AIC of Bayesian model.
np	equivalent number of parameters.
pacoef.bay	partial autocorrelation coefficients of Bayesian model.
arcoef	AR coefficients of Bayesian model.
pspec	power spectrum.

References

H.Akaike (1978) A Bayesian Extension of The Minimum AIC Procedure of Autoregressive model Fitting. Research memo. No.126. The Institute of Statistical Mathematics.

G.Kitagawa and H.Akaike (1978) A Procedure for The Modeling of Non-Stationary Time Series. Ann. Inst. Statist. Math., 30, B, 351–363.

H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Tim-sac78*. The Institute of Statistical Mathematics.

Examples

```
data(Canadianlynx)
z <- unibar(Canadianlynx, ar.order = 20)
z$arcoef
```

unimar

*Univariate Case of Minimum AIC Method of AR Model Fitting***Description**

This is the basic program for the fitting of autoregressive models of successively higher by the method of least squares realized through householder transformation.

Usage

```
unimar(y, max.order = NULL, plot = FALSE)
```

Arguments

<code>y</code>	a univariate time series.
<code>max.order</code>	upper limit of AR order. Default is $2\sqrt{n}$, where n is the length of the time series y .
<code>plot</code>	logical. If TRUE, daic is plotted.

Details

The AR model is given by

$$y(t) = a(1)y(t-1) + \dots + a(p)y(t-p) + u(t),$$

where p is AR order and $u(t)$ is Gaussian white noise with mean 0 and variance v . AIC is defined by

$$AIC = n \log(\det(v)) + 2k,$$

where n is the length of data, v is the estimates of the innovation variance and k is the number of parameter.

Value

<code>mean</code>	mean.
<code>var</code>	variance.
<code>v</code>	innovation variance.
<code>aic</code>	AIC.
<code>aicmin</code>	minimum AIC.
<code>daic</code>	AIC-aicmin.
<code>order.maice</code>	order of minimum AIC.
<code>v.maice</code>	innovation variance attained at order.maice.
<code>arcoef</code>	AR coefficients.

References

G.Kitagawa and H.Akaike (1978) A Procedure For The Modeling of Non-Stationary Time Series. *Ann. Inst. Statist. Math.*,30, B, 351–363.

H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Tim-sac78*. The Institute of Statistical Mathematics.

Examples

```
data(Canadianlynx)
z <- unimar(Canadianlynx, max.order = 20)
z$arcoef
```

wnoise	<i>White Noise Generator</i>
--------	------------------------------

Description

Generate approximately Gaussian vector white noise.

Usage

```
wnoise(len, perr, plot = TRUE)
```

Arguments

len	length of white noise record.
perr	prediction error.
plot	logical. If TRUE (default), white noises are plotted.

Value

wnoise gives white noises.

References

H.Akaike and T.Nakagawa (1988) *Statistical Analysis and Control of Dynamic Systems*. Kluwer Academic publishers.

Examples

```
# Example 1
wnoise(len = 100, perr = 1)

# Example 2
v <- matrix(c(1, 0, 0,
              0, 2, 0,
              0, 0, 3), nrow = 3, ncol = 3, byrow = TRUE)
wnoise(len = 20, perr = v)
```

xsarma

*Exact Maximum Likelihood Method of Scalar ARMA Model Fitting***Description**

Produce exact maximum likelihood estimates of the parameters of a scalar ARMA model.

Usage

```
xsarma(y, arcoefi, macoefi)
```

Arguments

y	a univariate time series.
arcoefi	initial estimates of AR coefficients.
macoefi	initial estimates of MA coefficients.

Details

The ARMA model is given by

$$y(t) - a(1)y(t-1) - \dots - a(p)y(t-p) = u(t) - b(1)u(t-1) - \dots - b(q)u(t-q),$$

where p is AR order, q is MA order and $u(t)$ is a zero mean white noise.

Value

gradi	initial gradient.
lkhoodi	initial (-2)log likelihood.
arcoef	final estimates of AR coefficients.
macoef	final estimates of MA coefficients.
grad	final gradient.
alph.ar	final ALPH (AR part) at subroutine ARCHCK.
alph.ma	final ALPH (MA part) at subroutine ARCHCK.
lkhood	final (-2)log likelihood.
wnoise.var	white noise variance.

References

H.Akaike (1978) Covariance matrix computation of the state variable of a stationary Gaussian process. Research Memo. No.139. The Institute of Statistical Mathematics.

H.Akaike, G.Kitagawa, E.Arahata and F.Tada (1979) *Computer Science Monograph, No.11, Tim-sac78*. The Institute of Statistical Mathematics.

Examples

```
# "arma.sim" is a function in "stats".
# Note that the sign of MA coefficient is opposite from that in "timsac".
arcoef <- c(1.45, -0.9)
macoef <- c(-0.5)
y <- arima.sim(list(order=c(2,0,1), ar=arcoef, ma=macoef), n = 100)
arcoefi <- c(1.5, -0.8)
macoefi <- c(0.0)
z <- xsarma(y, arcoefi, macoefi)
z$arcoef
z$macoef
```

Index

* datasets

Airpollution, 3
Amerikamaru, 4
bispecData, 11
Blsallfood, 14
Canadianlynx, 17
LaborData, 28
locarData, 29
nonstData, 46
Powerplant, 51

* package

timsac-package, 3

* ts

armafit, 4
auspec, 5
autcor, 6
autoarmafit, 7
baysea, 8
bispec, 10
blocar, 12
blomar, 13
bsubst, 15
canarm, 18
canoca, 19
covgen, 21
decomp, 21
exsar, 24
fftcor, 25
fpeaut, 26
fpec, 27
markov, 29
mfilter, 31
mlocar, 32
mlomar, 34
mulbar, 35
mulcor, 37
mulfrf, 38
mulmar, 39
mulnos, 41

mulrsp, 42
mulspe, 43
nonst, 45
optdes, 46
optsim, 47
perars, 49
plot.decomp, 50
plot.specmx, 51
prdctr, 52
raspec, 53
sglfre, 54
simcon, 55
thirmo, 57
unibar, 58
unimar, 60
wnoise, 61
xsarma, 62

Airpollution, 3
Amerikamaru, 4
arma.sim, 31
armafit, 4
auspec, 5
autcor, 6
autoarmafit, 7

baysea, 8
bispec, 10, 11
bispecData, 11
blocar, 12, 29
blomar, 4, 13
Blsallfood, 14
bsubst, 15, 17

Canadianlynx, 17
canarm, 18
canoca, 19
convolve, 31
covgen, 21
decomp, 21, 50

exsar, [17](#), [24](#)

fftcors, [25](#)
fpeaut, [26](#)
fpec, [27](#)

LaborData, [28](#)
locarData, [29](#)

markov, [29](#)
mfilter, [31](#)
mlocar, [29](#), [32](#)
mlomar, [34](#)
mulbar, [35](#), [51](#)
mulcor, [37](#)
mulfrf, [38](#)
mulmar, [39](#), [51](#)
mulnos, [41](#)
mulrsp, [42](#), [51](#)
mulspe, [43](#), [51](#)

nonst, [45](#), [46](#)
nonstData, [46](#)

optdes, [46](#)
optsim, [47](#)

perars, [3](#), [49](#)
plot.decomp, [22](#), [50](#)
plot.specmx, [42](#), [44](#), [51](#)
Powerplant, [51](#)
prdctr, [52](#)
print.autoarmafit (autoarmafit), [7](#)
print.blomar (blomar), [13](#)
print.fpec (fpec), [27](#)
print.mlomar (mlomar), [34](#)
print.mulcor (mulcor), [37](#)
print.perars (perars), [49](#)
print.prdctr (prdctr), [52](#)
ptint.mulspe (mulspe), [43](#)

raspec, [53](#)

sglfre, [54](#)
simcon, [29](#), [55](#)

thirmo, [11](#), [57](#)
timsac (timsac-package), [3](#)
timsac-package, [3](#)

unibar, [17](#), [58](#)

unimar, [17](#), [60](#)
wnoise, [61](#)
xsarma, [62](#)